



NOTE: If rec. has been modified for factory C.G., and is the Early Production 2W audio type, make sure R41 (200K) is re-added between the +10v regulated keyed supply and the base of the DC AMP Q8.....

APPLICATION PARTS (not supplied)

- 1- 100K 1/4 watt
- 1- .luf-12V capacitor
- 1- set mounting hardware and wires

If you are using the audio filter try leaving in JU-2 instead of clamping the squelch with OUT-1 or OUT-2 as shown on the hook-up.

NOTE:
Early production IF board-2W audio
 JU-1, in
 Use OUT 2, hook to J11 (base of DC amp)
Late production IF board-5w audio
 JU-1, in
 Use OUT 2,
 Hook to collector of DC amp (J11 is hooked to base to identify proper xistor).

JU-1 (in)
 JU-2 (out)

SPECIAL NOTICE

WHEN MOUNTING THE TS-32 WITH A 90 DEGREE ANGLE BRACKET AGAINST THE PCB, BE SURE TO USE THE TWO FIBER SPACERS PROVIDED BETWEEN ANGLE BRACKET AND PCB. IF THIS IS NOT DONE, THE BRACKET WILL SHORT OUT FOILS ON THE PCB.....